



MX Series

Compact, efficient and reliable, these professional generators are equipped with a powerful and economic engine. Combining endurance and functionality, they are the perfect tool for an intensive use.



Main applications:

- Construction
- Road works
- Industrial applications



**OPTIONAL:
MANUAL TRANSFER SWITCH 40A
(FOR MANUAL CONTROL VERSIONS 230V)**



**READY TO USE.
TRANSPORTATION KIT ALREADY ASSEMBLED,
NO TOOLS REQUIRED**



**INCREASED AUTONOMY THROUGH THE BIG
FUEL TANK INTEGRATED METAL FROM 18,5 TO
25,5 LITERS WITH FUEL GAUGE**



**QUICK START SLIDE-OUT INSTRUCTION GUIDE
LOCATED BELOW THE CONTROL PANEL**



COMPLETE CONTROL PANEL

GENERATING SET	MX 3000	MX 5000	MX 8000
MAIN DATA	SINGLE PHASE	SINGLE PHASE	SINGLE PHASE
POWER RATING - SINGLE PHASE	kVA / kWe	kVA / kWe	kVA / kWe
STAND BY POWER - LTP	2,6 / 2,3	4,5 / 4,1	6,9 / 6,2
CONTINUOUS POWER - COP	2,0 / 1,8	3,7 / 3,3	5,9 / 5,4
VOLTAGE (Volt)	230	230	230
FREQUENCY (Hz)	50	50	50
POWER FACTOR (Cos Φ)	0,9	0,9	0,9
ENGINE			
BRAND	Honda	Honda	Honda
MODEL	GX160	GX270	GX390
FUEL	Petrol	Petrol	Petrol
CYLINDERS / DISPLACEMENT (cc)	1 inclined / 163	1 inclined / 270	1 inclined / 389
COOLING SYSTEM	Air	Air	Air
STARTING SYSTEM	Recoil	Recoil	Recoil Electric (+Recoil)
SPEED (rpm)	3000	3000	3000
CONSUMPTION			
FUEL CONSUMPTION at 75% of load (L/h)	0,88	1,36	2,00
FUEL TANK CAPACITY (L)	18,5	25,5	25,5
RUNNING TIME at 75% of load (h)	21,02	18,75	12,75
OVERALL DIMENSIONS			
LENGTH (mm)	600	727	727
WIDTH (mm)	439	515	515
HEIGHT (mm)	588	670	670
DRY WEIGHT (Kg)	53	79	94 100
STANDARD EQUIPMENT			
DIGITAL DISPLAY	V - Hz- h	V - Hz- h	V - Hz- h
ANALOG INSTRUMENTS	Fuel gauge	Fuel gauge	Fuel gauge
TANK (Type)	Metal	Metal	Metal
SOCKETS	2 x 230V SCHUKO 16A IP54	2 x 230V SCHUKO 16A IP54 1 x 230V CEE 16A IP44	1 x 230V SCHUKO 16A IP54 1 x 230V CEE 16A IP44 1 x 230V CEE 32A IP44
TRANSPORTATION KIT	Standard	Standard	Standard
AVR - AUTOMATIC VOLTAGE REGULATOR	Standard	Standard	Standard
PROTECTIONS			
OIL GUARD	Standard	Standard	Standard
THERMAL PROTECTION	Standard	Standard	Standard
ALTERNATOR PROTECTION (IP)	23	23	23
OPTIONALS			
MTS- MANUAL TRANSFER SWITCH	o	o	o

o = Accessory available



www.masonsgenerators.com

MASONS DISTRIBUTOR IN YOUR AREA IS:

PR MIDDLE EAST FZE

1206 JAFZA View 18, P.O. Box 262478 - Jebel Ali Free Zone - South 1, Dubai
Tel.: +971 4 8865275 - Fax: +971 4 8865276